



8 7 6 5 4 3 2 1

ALL PLUG DETAILS ON PAGE 2 DO NOT PRODUCE PRODUCTION PARTS FROM DRAWINGS THAT ARE MARKED "PROTOTYPE"

REV	DESCRIPTION	DATE	APPROVED
00	PROTOTYPE RELEASE	1/25/08	
0	PRODUCTION RELEASE	p4/01/08	


**APPROVED
RELEASED FOR
PRODUCTION USE**

PLUG "A" 8 WAY 14/16 GA. DEUTSCH PLUG CONNECTOR W/RECP
DETAIL DT06-08SA TO SWITCH PANEL 65-0810 PLUG "A"




1. 16 GA GRAY NAV *LT*
2. 16 GA GRAY/WHITE ANC *LT*
3. 16 GA BROWN MAN *BILGE*
4. 16 GA BROWN/WHITE BAIT
5. 16 GA PINK FUEL
6. HOLE PLUG 114017
7. HOLE PLUG 114017
8. HOLE PLUG 114017

PLUG "C" 2 WAY, 14/16 GA DEUTSCH PLUG CONNECTOR W/RECEPS
DETAIL DT06-2S NAV *LT*






1. 16 GA GRAY NAV *LT*
2. 16 GA BLACK

PLUG "D" 2 WAY, 14/16 GA DEUTSCH PLUG CONNECTOR W/RECEPS
DETAIL DT06-2S ANC *LT*




1. 16 GA GRAY/WHITE ANC *LT*
2. 16 GA BLACK

PLUG "E" 3 WAY, 14/16 GA DEUTSCH PLUG CONNECTOR W/RECEPS
DETAIL DT06-3S BILGE



- 16 GA BROWN MAN *BILGE*
- 16 GA BROWN/RED AUTO *BILGE*
- 16 GA BLACK

PLUG "F" 2 WAY, 14/16 GA DEUTSCH PLUG CONNECTOR W/RECEPS
DETAIL DT06-2S BAIT



1. 16 GA BROWN/WHITE BAIT
2. 16 GA BLACK

FUSE COVER DETAIL "H"

AUTO *BILGE*

14 BRN/RED 14"

2X 44

3A

45

46

43

14 BRN/RED 82"

9

NOTES:

1. SPOT TAPE EVERY 12 INCHES.
2. LABEL WIRES WHERE IS LOCATED ON BOTH ENDS.

30 AMP SURFACE MOUNT BREAKER DETAIL "G"

INSTALL TWO SMALL RED BOOTS (4702) ON EACH 10 GA RED WIRE THAT LAND ON 30 AMP BREAKER

10 RED 18"

10 RED 14"

10 RED 10/12 RING 3/8" HS


30 AMP

BATTERY 10 RED

10/12 RING 1/4" HS

42

INSTALL BOOTS HERE ON 10/12 RING 1/4" HS



PHAZE II PRODUCTS

118 PENNSYLVANIA VIRGINIA BEACH, VA 23462
PHONE: 757-353-3901
FAX: 757-353-3903

DRN BY: RICHARD B.

CHK BY:

SHEET: 2 OF 4

DATE DRAWN: 04-01-2008

SCALE: FULL

DWG NO.: 65-0802

REVISION: 0

WWW.PHAZE2PRODUCTS.COM

SUNDANCE BOATS

23V ACCESSORY HARNESS

PLUGS, FUSE HOLDERS DETAILS

THIS DOCUMENT IS THE PROPERTY OF PHAZE II PRODUCTS, INC. ANY INFORMATION, SPECS, OR DESIGNS MAY NOT BE COPIED OR USED IN ANY MANNER WITHOUT THE WRITTEN PERMISSION OF PHAZE II PRODUCTS, INC. AND IT MUST BE RETURNED UPON REQUEST. ANY UNAUTHORIZED USE OF THIS DOCUMENT WILL RESULT IN LEGAL ACTION AND LITIGATION.